Install Student Lounge Printers (Meridian)

For MAC OS 10.4 and higher

- 1. Download the following software: https://pharmacy.isu.edu/tech/HPPrinterDrivers.dmg
 - Open the file
 - Double click HewlettPackardPrintDrivers.pkg
 - Select Continue twice and agree the terms
 - Once the software is done select Done.
- 2. Go to System Preferences



3. Choose Printers & Scanners



- 4. Hit the + symbol in the bottom left
- 5. Select the IP tab in the top left

• •	•			Add			
Q			÷Of	Q Search			
Default	IP	Windows	Advanced		Search		
A	\ddress	:					
		Enter hos	t name or IP	address.			
P	rotocol	: Interne	et Printing F	Protocol - IPP		<	3
	Queue	:					
	Name	e					
L	ocation	:					
	Use	e (<	3
						Ada	
						Add	1

- 6. Enter in the address: **10.255.96.1** (Printer 1) and **10.255.96.2** (Printer 2 the second time we do this).
 - a. NOTE: Make sure to select for Protocol: HP Jetdirect -- Socket
- 7. Click on the drop down in the "Use:" field and choose Select Software



8. Type in 608 in the search bar and select HP LaserJet 607 M607 M608 M609 and click OK

Printer Software					
		_			
	Q 608	8			
HP LaserJet M607 M608 M609					
	Cancel OK				

9. In the name field type in a name that you will recognize as the pharmacy printer 1. Below is an example of how the screen should look for Printer 1.

• • •				Add				
e		1	-Qr	Q Search				
Default IP	Win	dows	Advanced			Search		
Addre	ess: 1	0.255.9	96.1					
	Va	lid and	complete ho	st name or a	ddress.			
Proto	col:	HP Jet	direct - So	cket				٥
Queue:								
	Le	ave bla	nk for defaul	t queue.				
Na	me: P	harma	cy Student	t Printer 1				
Locat	ion:							
ι	Jse:	HP Las	erJet M60	7 M608 M6	609			0
							A	٨dd

10.Click the Add button and the following screen should appear. Make sure to check Duplex Unit (This allows for double sided printing) and select HP 2100-Sheet Input Tray for Tray 3

	Setting up '10.255.96.1'							
	Make sure your printer's options are accurately shown here so you can take full advantage of them.							
	Tray 3:	HP 2100-Sheet Input Tra	у ᅌ					
	Tray 4:	Not Installed	٥					
	Tray 5:	Not Installed	0					
	Tray 6:	Not Installed	0					
ŀ	IP 5-Bin Stapler/Stacker:	Not Installed	0					
		🗹 Duplex Unit						
		Cancel	ОК					

11.Please repeat instructions 2-10 to add printer 2.